

# Installing the driver

Copyright © 2007 ROLAND CORPORATION  
All rights reserved. No part of this publication may be reproduced in any form without the written permission of ROLAND CORPORATION.



**Disconnect your USB devices**  
Disconnect all USB cables from your computer, except for a USB keyboard and/or USB mouse (if used). Do not connect the V-Synth GT to your computer yet.

**Close all software**  
Close all software and utility programs including anti-virus software.


In order to connect the V-Synth GT to your computer and use it, you must install the driver and make settings.

**Proceed to the next step as appropriate for your operating system.**

See other side **Mac OS X**

## Windows XP

### 1 Preparations for installation



- 1 Insert the included CD-ROM into your computer.
- 2 Start up the driver installer.
  1. Choose [Start] — [My Computer].
  2. Double-click "DVD/CD-ROM drive."
  3. Double-click the DRIVER folder.
  4. Double-click the XP folder.
  5. Double-click the Setup icon.
- 3 Click [Next] as instructed by the "Driver Setup" dialog box.
  1. The "Driver Setup" dialog box will appear. Click [Next] as directed in the screen.
  2. To begin the installation, click [Next] once again.

If a dialog box regarding Windows logo testing appears, click [Continue Anyway].

- 3. The "Roland V-Synth GT Driver will be installed on your computer" dialog box will appear.

This completes the preparations for installing the driver.

### 2 Driver installation and connections



- 1 Use a USB cable to connect the V-Synth GT to your computer.
  1. Switch off the power on the V-Synth GT.
  2. Use a USB cable to connect the V-Synth GT to your computer.
- 2 Power up the V-Synth GT.
  1. Switch on the power on the V-Synth GT.
  2. The message "Found New Hardware" will appear near the taskbar, and then the "Found New Hardware Wizard" will appear.

If the Found New Hardware Wizard asks whether you want to connect to Windows Update, choose "No, ..." and click [Next].
- 3 Choose the installation method.
  1. Choose "Install the software automatically (Recommended)," and click [Next].

If a dialog box regarding Windows logo testing appears, click [Continue Anyway].
- 4 Click [Finish] to complete the installation.
  1. Make sure that "Roland V-Synth GT" is displayed, and click [Finish].
  2. In the "Driver Setup" dialog box, click [Close].
  3. If the "System Settings Change" dialog box appears, click [Yes].
  4. Restart Windows.

This completes the driver installation.

### 3 Performance Options settings

By making these settings you may be able to prevent clicks or pops in the sound. Be sure to make the settings as described below.



- 1 Open the System Properties dialog box.
  1. Choose [Start] — [Control Panel]. The control panel will open.
  2. If the screen indicates "Pick a category," click [Performance and Maintenance].
  3. In "or pick a Control Panel icon," click the [System] icon.
- 2 Open the Performance Options dialog box.
  1. Click the "Advanced" tab, and in the "Performance" area, click [Settings].
- 3 Enable "Background services."
  1. Click the "Advanced" tab.
  2. In the "Processor scheduling" area, choose "Background services" and click [OK].
  3. In the System Properties dialog box, click [OK].

This completes the performance options settings.


### 4 Input/output device settings

In order to take full advantage of your software, make input/output device settings for your software as described below. For details on the procedure, refer to the user's guide for the software you're using.

|                        |   |
|------------------------|---|
| <b>MIDI OUT device</b> | Roland V-Synth GT   |
| <b>MIDI IN device</b>  | Roland V-Synth GT   |
| <b>WAVE OUT device</b> | Roland V-Synth GT   |
| <b>WAVE IN device</b>  | Roland V-Synth GT<br>* This receives audio signals sent from the V-Synth GT to your computer.   |
| <b>ASIO device</b>     | If you're using the V-Synth GT with an ASIO-compatible application such as Cubase, choose "Roland V-Synth GT" for the ASIO settings of your application.<br>To prevent audio feedback loops or double monitoring, turn off monitoring in your application, or set things so ASIO Direct Monitoring is used.<br>* The V-Synth GT does not support ASIO Direct Monitoring. Support is emulated for your convenience.<br>* If you're using the V-Synth GT with ASIO, we recommend that you make settings in your application so that the Microsoft GS Wavetable SW Synth is not used. (This is in order to decrease the processor load, and for convenience in changing the buffer size of the driver.)<br>* In Cubase SX, if the V-Synth GT's sampling frequency is different than Cubase SX's project setting, a message such as "Sample could not be set" may appear, and you will be unable to record or play back correctly. If this occurs, you can ensure correct operation by opening "Project Setup," making sure that the sampling frequency matches, and clicking [OK]. |

## Windows Vista


### 1 Preparations for installation



- 1 Insert the included CD-ROM into your computer.
- 2 Start up the installer driver.
  1. Choose [Start] — [Computer].
  2. Double-click "DVD/CD-ROM drive."
  3. Double-click the DRIVER folder.
  4. Double-click the Vista folder.
  5. Double-click the Setup icon.
- 3 If a User Account Control screen appears, click [Continue].  
If the screen indicates "Driver installation must be performed by an administrator," you must log on to Windows as a user whose account type is Administrator, and perform the installation again.

This completes the preparations for installing the driver.

### 2 Driver installation and connections



- 1 The screen will indicate "Roland V-Synth GT Driver will be installed on your computer."
    1. Click [Next].

If a different message appears, proceed as directed by that message.

  - 2. To begin the installation, click [Next].
- 2 If a Windows Security dialog box appears, click [Install].
    1. The screen will indicate "The V-Synth GT driver has been installed."

If a different message appears, proceed as directed by that message.
  - 3 Use a USB cable to connect the V-Synth GT to your computer.
    1. Turn off the power on the V-Synth GT.
    2. Use a USB cable to connect the V-Synth GT to your computer.
  - 4 Turn on the power on the V-Synth GT.
    1. Turn on the power on the V-Synth GT.
    2. The message "Installing device driver software" will appear near the taskbar, and the driver will be installed automatically.


If a different message appears, proceed as directed by that message.

  - 3. Installation is complete when the screen indicates "Device driver software installed successfully."
- 5 Click [Close] to complete the installation.
    1. In the "Driver Setup" dialog box, click [Close].
    2. If the "System Settings Change" dialog box appears, click [Yes] to restart Windows.

This completes the driver installation.

### 3 Performance Options settings

By making these settings you may be able to prevent clicks or pops in the sound. Be sure to make the settings as described below.



- 1 Open the System Properties dialog box.
  1. Choose [Start] — [Control Panel]. The control panel will open.
  2. Click [System and Maintenance].
  3. Then click the [System] icon.
- 2 In the area at left, click "Advanced system settings."
- 3 If a User Account Control screen appears, click [Continue].  
If you are asked to enter the password of an Administrator account, log on to Windows as a user whose account type is Administrator, and then make the settings again.
- 4 Open the performance options dialog box.
  1. Click the "Advanced" tab, and in the Performance area click [Settings].
- 5 Enable "Background services."
  1. Click the "Advanced" tab.
  2. In the "Processor scheduling" area, choose "Background services" and click [OK].
  3. In the System Properties dialog box, click [OK] to close System Properties.

This completes the performance options settings.

### 4 Input/output device settings

In order to take full advantage of your software, make input/output device settings for your software as described below. For details on the procedure, refer to the user's guide for the software you're using. The audio input/output of the V-Synth GT is 2-in/2-out.

|                        |  |
|------------------------|--|
| <b>WAVE OUT device</b> | OUT (Roland V-Synth GT)<br>If you've renamed this in the control panel "Sound" settings, the name you specified will appear. In WDM/KS compatible applications such as Cakewalk SONAR, this will appear as "Roland V-Synth GT."  |
| <b>WAVE IN device</b>  | IN (Roland V-Synth GT)<br>If you've renamed this in the control panel "Sound" settings, the name you specified will appear. In WDM/KS compatible applications such as Cakewalk SONAR, this will appear as "Roland V-Synth GT."   |
| <b>ASIO device</b>     | If you're using the V-Synth GT with an ASIO-compatible application such as Cubase, choose "Roland V-Synth GT" for the ASIO settings of your application.<br>* To prevent audio feedback loops or double monitoring, turn off monitoring in your application, or set things so ASIO Direct Monitoring is used.<br>* The V-Synth GT does not support ASIO Direct Monitoring. Support is emulated for your convenience.<br>* If you're using the V-Synth GT with ASIO, we recommend that you make settings in your application so that the Microsoft GS Wavetable SW Synth is not used. (This is in order to decrease the processor load, and for convenience in changing the buffer size of the driver.) |

# Mac OS X

## 1 Driver installation



- 1 Insert the included CD-ROM into your Mac.
- 2 Start up the Mac driver installer.
  1. Double-click V-SYNTH GT DRIVER CD-ROM.
  2. Double-click the V-SYNTH GT Driver OS X folder.
  3. Double-click VSynthGTUSBDriver.pkg.
- 3 As directed by the "Install Roland V-Synth GT Driver" screen, click [Continue].
  1. "Install Roland V-Synth GT Driver" will appear; click [Continue] as directed in the screen.
  2. When "Select a Destination" appears, select the startup disk, and click [Continue].
  3. When "Easy Install" appears, click [Install] (or [Upgrade]).  
If an authentication dialog box appears, enter the password you use for Mac OS, and click [OK].
  4. When "Installing this software requires you to restart ~" appears, click [Continue Installation].
  5. When you see "The software was successfully installed," click [Restart] to restart your Mac.

This completes the driver installation.

## 2 Connecting the V-Synth GT to your Mac

- 1 Use a USB cable to connect the V-Synth GT to your Mac.
  1. Switch OFF the V-Synth GT's power switch (POWER).
  2. Use a USB cable to connect the V-Synth GT to your Mac.  
Connect the cable to a USB connector on the Mac itself (not to the USB connector on your keyboard).
- 2 Switch on the V-Synth GT's power.
  1. Turn the V-Synth GT's power switch ON.

This completes the connections between the V-Synth GT and your Mac.

## 3 Audio input/output settings



- 1 In the Mac OS "System Preferences," click "Sound."
- 2 Choose "Roland V-Synth GT 44.1 kHz" for the following items.
  1. Sound Effects tab "Play alerts and sound effects through"
  2. Output tab "Choose a device for sound output"
  3. Input tab "Choose a device for sound input"

This completes the audio input/output settings.

## 4 MIDI input/output settings



- 1 Start up Audio MIDI settings and make the settings.
  1. In the Mac OS Applications — Utilities folder, double-click Audio MIDI Setup.
  2. Click the MIDI Devices tab.
  3. In the Audio MIDI Setup dialog box, make sure that "V-Synth GT" is shown.  
If "V-Synth GT" is not shown, or is grayed-out, the V-Synth GT has not been detected correctly. Try clicking "Re-scan MIDI." Also try powering the V-Synth GT off, then on again.
- 2 Add "V-Synth GT" as an external device.
  1. Click "Add Device." The screen will indicate "new external device."
- 3 For "new external device," change "Device Name" to V-Synth GT.
  1. Click the added "new external device" to select it, and click "Show Info."
  2. In the "Device Name" field, enter "V-Synth GT" and close the dialog box.
- 4 Connect the up/down arrows that indicate input/output ports as follows.
  1. Using the mouse, drag the up/down arrows of the originally shown "V-Synth GT" to connect them to the up/down arrows of the newly added "V-Synth GT"
- 5 Verify that MIDI transmission/reception is occurring correctly.
  1. Click "Test Setup." The mouse cursor will change to the shape of a musical note.
  2. Click the newly added V-Synth GT. If the sound generator produces sound, the settings have been made correctly.  
The following step will cause the sound generator to produce a fairly loud sound, so please turn down the volume of the sound generator before you continue.
- 6 Click "Test Setup" once again to finish the test.
  1. Close the Audio MIDI Setup dialog box to finish the settings.

This completes the MIDI input/output settings.

## 5 If you're using the V-Synth GT from within software

- 1 Use a USB cable to connect the V-Synth GT to your Mac, and then start up your software.
- 2 In the Audio Driver settings of the software you're using, choose "Roland V-Synth GT 44.1 kHz."
- 3 In the MIDI Driver settings of the software you're using, choose V-Synth GT.

For details on how to make these settings, refer to the user's guide for the software you're using.



## Troubleshooting

Check the following items first. For other problems, or for directions on how to uninstall the driver, refer to Readme\_E.htm on the CD-ROM.

Visit us online at [www.Roland.com](http://www.Roland.com)

### Can't install the driver

- Did you log on to Windows with the appropriate user privileges?  
You must log on to Windows as a user whose account type is Administrator.

### Can't select/use the V-Synth GT device

- Is the driver correctly installed?  
If you're unable to use the V-Synth GT even though the driver was installed, it is possible that the driver was not installed correctly. Re-install the driver following the correct procedure.
- Is the V-Synth GT's MIDI/WAVE device name displayed?  
If you're using Windows and the device name is not displayed, close all applications that are using the V-Synth GT, switch off the V-Synth GT's power, then turn it back on again. If this does not solve the problem, install the driver once again.
- Could your computer have entered Sleep or Standby (Suspend) mode while the V-Synth GT was powered up and connected?  
If the V-Synth GT does not operate correctly after your computer returns from Sleep or Standby (Suspend) mode, close all the software you're using, and then turn the V-Synth GT's power off, then on again.
- While using the V-Synth GT, could you have disconnected and reconnected the USB cable or switched the V-Synth GT's power off, then on again?  
If you disconnect and reconnect the USB cable or cycle the power to the V-Synth GT during use, it may stop operating correctly. In this case, close all the software you're using, and then turn the V-Synth GT's power off, then on again.

- On some computers, if Windows is started up when the V-Synth GT is already connected, the driver might not be loaded correctly, making it impossible to use the V-Synth GT via USB.  
In this case, turn on the V-Synth GT's power after Windows has started up, or connect it after Windows has started up.

### A number such as "2-" is now displayed at the beginning of the device name

- Could you have connected the V-Synth GT to a different USB port?  
If you connect the V-Synth GT to a different USB port, the operating system may automatically add a number to the beginning of the device name. This should not be a cause for concern when using the V-Synth GT.



## Information

When you need repair service, call your nearest Roland Service Center or authorized Roland distributor in your country as shown below.

### AFRICA

**EGYPT**  
Al Fanny Trading Office  
9, El-Fayyaz, El-Askalany  
Street,  
Cairo 11541, EGYPT  
TEL: 20-2-417-1828

**REUNION**  
Maison FO - YAM Marcel  
25 Rue Jules Hermain,  
Chaudron - BP79 97 491  
St. Clotilde Cedex,  
REUNION ISLAND  
TEL: (0262) 218-429

**SOUTH AFRICA**  
T.D.M.S. Sound & Music  
(Pty) Ltd.  
2 ASTRON ROAD DENVER  
JOHANNESBURG ZA 2195,  
SOUTH AFRICA  
TEL: (011) 417 3400  
FAX: (011) 417 3462

Paul Bothner(PTY) Ltd.  
Royal Cape Park, Unit 24  
Londonderry Road, Ottery 7800  
Cape Town, SOUTH AFRICA  
TEL: (021) 799 4900

### ASIA

**CHINA**  
Roland Shanghai Electronics  
Co., Ltd.  
5F, No.1500 Pingliang Road  
Shanghai 200090, CHINA  
TEL: (021) 5580-8800

**ROLAND (SHANGHAI) ELECTRONICS  
CO., LTD.**  
BEIJING OFFICE  
10F, No.18 3 Section Anhuaxili  
Chaoyang District Beijing  
100011 CHINA  
TEL: (010) 6426-5050

**HONG KONG**  
Tom Lee Music Co., Ltd.  
Service Division  
22-32 Pun Shan Street, Tuen  
Wan, New Territories,  
HONG KONG  
TEL: 2415 0911

**Parsons Music Ltd.**  
8th Floor, Railway Plaza, 39  
Chatham Road South, T.S.T.,  
Kowloon, HONG KONG  
TEL: 2333 1883

### INDIA

Rivers Digital (India) Pvt. Ltd.  
409, Nirman Kendra  
Mahaximi Flats Compound  
Off. Dr. Edwin Moses Road,  
Mumbai-400011, INDIA  
TEL: (022) 2493 9051

**INDONESIA**  
PT Citra IntiRama  
Jl. Cikendang Timur No. 151-150  
Jakarta Pusat  
INDONESIA  
TEL: (021) 6324170

### KOREA

**KOREA**  
Cosmos Corporation  
1461-9, Seocho-Dong,  
Seocho-Ku, Seoul, KOREA  
TEL: (02) 3486-8855

**MALAYSIA**  
Roland Asia Pacific Sdn. Bhd.  
45-1, Block C2, Jalan PJU 1/39,  
Dataran Prima, 47301 Petaling  
Jaya, Selangor, MALAYSIA  
TEL: (03) 7805-3263

### PHILIPPINES

G.A. Yurpango & Co. Inc.  
339 Gilj, Payat Avenue  
Makati, Metro Manila 1200,  
PHILIPPINES  
TEL: (02) 899 9801

**SINGAPORE**  
SWEET LEE MUSIC  
COMPANY PTE. LTD.  
150 Sims Drive,  
SINGAPORE 387381  
TEL: 8866-3676

**TAIWAN**  
ROLAND TAIWAN  
ENTERPRISE CO., LTD.  
Room 5, 9th, No. 112 Chung  
Shan N. Road Sec. 2, Taipei,  
TAIWAN, R.O.C.  
TEL: (02) 2561 3339

**THAILAND**  
Theera Music Co., Ltd.  
330 Soi Veeng NakornKasem,  
New Road, Sumpantawongse,  
Bangkok 10100, THAILAND  
TEL: (02) 224-8821

### AUSTRALIA/NEW ZEALAND

**AUSTRALIA/NEW ZEALAND**  
Roland Corporation  
Australia Pty. Ltd.  
38 Campbell Avenue,  
Dee Why West, NSW 2099  
AUSTRALIA  
Tel: (02) 9982 8266  
For New Zealand  
Tel: (09) 3098 715

### CENTRAL/LATIN AMERICA

**ARGENTINA**  
Instrumentos Musicales S.A.  
Av. Santa Fe 2055  
(1123) Buenos Aires  
ARGENTINA  
TEL: (011) 4508-2700

**BARBADOS**  
A&B Music Supplies LTD  
12 Webster Industrial Park  
Wilkey, St. Michael, Barbados  
TEL: (246)430-1100

**BRAZIL**  
Roland Brasil Ltda.  
Rua San Jose, 780 Sala B  
Parque Industrial San Jose  
Cotia - Sao Paulo - SP, BRAZIL  
TEL: (011) 4615 5666

**CHILE**  
Comercial Fancy II S.A.  
Rat. 96319 420-1  
Natalien Cox #739, 4th Floor  
Santiago - Centro, CHILE  
TEL: (02) 688-9540

**COLOMBIA**  
Centro Musical Ltda.  
Cra 43 B No 25 A 41 Bodegosa 9  
Medellin, Colombia  
TEL: (574)3812529

**COSTA RICA**  
JUAN BAMBACH Instrumentos  
Musicales  
Ave. 1, Calle 11, Apartado 10237,  
San Jose, COSTA RICA  
TEL: 258-0211

### CURACAO

Zerlandia Music Center Inc.  
Oniroweg 30  
Curacao, Netherland Antilles  
TEL: (305)926866

**DOMINICAN REPUBLIC**  
Instrumentos Fernando Giraldez  
Calle Proyecto Central No.3  
Esa La Esperilla  
Santo Domingo,  
Dominican Republic  
TEL: (809) 683 1335

**ECUADOR**  
Mas Musica  
Rumichaca 822 y Zaruma  
Guayaquil - Ecuador  
TEL: (593-43202364

**EL SALVADOR**  
ONINI MUSIC  
75 Avenida Norte y Final  
Alameda Juan Pablo II,  
Edificio No.4010 San Salvador,  
EL SALVADOR  
TEL: 262-0788

### EUROPE

**AUSTRIA**  
Roland Elektronische  
Musikinstrumente HmbH.  
Austrian Office  
Eduard-Hodmer-Gasse 8,  
A-6020 Innsbruck, AUSTRIA  
TEL: (0512) 26 44 260

**BELEM/FRANCE/HOLLAND/LUXEMBOURG**  
Roland Central Europe N.V.  
Houtstraat 3, B-2260, Oevel  
(Westerlo) BELGIUM  
TEL: (014) 575811

**CROATIA**  
ART-CENTAR  
Dugotova 3,  
CZECI REP.  
Vojtárova 247/16  
CZ - 180 00 PRAHA 8,  
CZECI REP.  
TEL: (2) 830 20270

**DENMARK**  
Roland Scandinavia A/S  
Nordhavnevej 7, Postbox 880,  
DK-2100 Copenhagen  
DENMARK  
TEL: 3916 6200

**FINLAND**  
Roland Scandinavia As, Finland  
Elmistonie 5,  
FIN-01510 Vantaa, FINLAND  
TEL: (09) 48 24 020

**GERMANY**  
Roland Elektronische  
Musikinstrumente HmbH.  
Oststrasse 96, 22844  
Norderstedt, GERMANY  
TEL: (040) 52 60900

**GREECE/CYPRUS**  
STOLLAS S.A.  
Music Sound Light  
155, New National Road  
Patras 2644, GREECE  
TEL: 2610 435400

**HUNGARY**  
Roland East Europe Ltd.  
Warehouse Area "DEPO" Pf.83  
H-2046 Tokobalint,  
HUNGARY  
TEL: (23) 511011

**IRELAND**  
Roland Ireland  
C2 Calmount Park, Calmount  
Avenue, Dublin 12,  
Republic of IRELAND  
TEL: (01) 4294444

**ITALY**  
Roland Italy S. p. a.  
Viale delle Industrie 8,  
20120 Arese, Milano, ITALY  
TEL: (02) 957-78300

### URUGUAY

Todo Musica S.A.  
Francisco Acuna de Figueroa  
1771  
C.P.: 11.800  
Montevideo, URUGUAY  
TEL: (02) 924 2335

**VENEZUELA**  
Instrumentos Musicales  
Allegro, C.A.  
Av. las Industrias edf. Guitar  
import  
#7 zona Industrial de Turumo  
Caracas, Venezuela  
TEL: (212) 244-1122

### NORWAY

Roland Scandinavia Avd.  
Kontor Norge  
Lillokerveien 2 Postboks 95  
Lilleaker N-0216 Oslo  
NORWAY  
TEL: 2275 0074

**POLAND**  
ROLAND POLSKA SP. Z O.O.  
UL. Gibraltar 4,  
PL-03 664 Warszawa  
POLAND  
TEL: (022) 679 4419

**PORTUGAL**  
Roland Iberia, S.L.  
Portugal Office  
Cais das Pedras, 8/7-1 Dto  
4005-645, Porto, PORTUGAL  
TEL: (21) 20-1441

**ROMANIA**  
FBS LINES  
Piata Libertatii 1,  
53000 Cheorgheni,  
ROMANIA  
TEL: (266) 364 669

**RUSSIA**  
MuTeK  
Donskoyaya ul.3, korp.6  
117 545 Moscow, RUSSIA  
TEL: (095) 981-4967

**SLOVAKIA**  
DAN Acoustic s.r.o.  
Fovarska 18  
SK - 940 01 Nove Zámky  
TEL: (035) 6424 330

**SPAIN**  
Roland Iberia, S.L.  
Paseo Garcia Faria, 33-35  
08005 Barcelona SPAIN  
TEL: 93 493 91 00

**SWEDEN**  
Roland Scandinavia A/S  
SWEDISH SALES OFFICE  
Duvick Center 28, 216  
S-131 30 Nacka SWEDEN  
TEL: (08) 702 00 20

**SWITZERLAND**  
Roland (Switzerland) AG  
Landstrasse 5, Postfach,  
CH-4142 Hingen,  
SWITZERLAND  
TEL: (061) 927-8383

**UKRAINE**  
EURIHYTHMICS Ltd.  
PO Box 37-4  
Nedecy Str. 30  
UA - 89600 Mukachovo,  
UKRAINE  
TEL: (03131) 414-40

**UNITED KINGDOM**  
Roland (U.K.) Ltd.  
Atlantic Close, Swansea  
Enterprise Park, SWANSEA  
SA7 9EJ,  
UNITED KINGDOM  
TEL: (01792) 702701

### SAUDI ARABIA

**SAUDI ARABIA**  
aDawlah Universal  
Electronics APL  
Corniche Road, Alodyssey  
Bldg., 1st Floor, Alkhobar,  
SAUDI ARABIA  
PO Box 2154, Alkhobar 31952  
SAUDI ARABIA  
TEL: (03) 898 2081

**SYRIA**  
Technical Light & Sound  
Center  
Rawda, Abdul Qader Jaziri St.  
Bldg. No. 21, P.O. BOX 13520,  
Damascus, SYRIA  
TEL: (011) 223-5384

**TURKEY**  
ZUHALDIS TICARET A.S.  
Galip Dede Cad. No.37  
Beyoglu - Istanbul / TURKEY  
TEL: (0212) 249 85 10

**U.A.E.**  
Zak Electronics & Musical  
Instruments Co. L.L.C.  
Zabool Road, Al Sheroq Bldg.,  
No. 14, Grand Floor, Dubai,  
U.A.E.  
TEL: (04) 3360715

### QATAR

**QATAR**  
Al Emadi Co. (Doha Studio &  
Stores)  
PO Box 62, Bada, QATAR  
TEL: 4423-554

**SAUDI ARABIA**  
aDawlah Universal  
Electronics APL  
Corniche Road, Alodyssey  
Bldg., 1st Floor, Alkhobar,  
SAUDI ARABIA  
PO Box 2154, Alkhobar 31952  
SAUDI ARABIA  
TEL: (03) 898 2081

**SYRIA**  
Technical Light & Sound  
Center  
Rawda, Abdul Qader Jaziri St.  
Bldg. No. 21, P.O. BOX 13520,  
Damascus, SYRIA  
TEL: (011) 223-5384

**TURKEY**  
ZUHALDIS TICARET A.S.  
Galip Dede Cad. No.37  
Beyoglu - Istanbul / TURKEY  
TEL: (0212) 249 85 10

**U.A.E.**  
Zak Electronics & Musical  
Instruments Co. L.L.C.  
Zabool Road, Al Sheroq Bldg.,  
No. 14, Grand Floor, Dubai,  
U.A.E.  
TEL: (04) 3360715

### SWITZERLAND

**SWITZERLAND**  
Roland (Switzerland) AG  
Landstrasse 5, Postfach,  
CH-4142 Hingen,  
SWITZERLAND  
TEL: (061) 927-8383

**UKRAINE**  
EURIHYTHMICS Ltd.  
PO Box 37-4  
Nedecy Str. 30  
UA - 89600 Mukachovo,  
UKRAINE  
TEL: (03131) 414-40

**UNITED KINGDOM**  
Roland (U.K.) Ltd.  
Atlantic Close, Swansea  
Enterprise Park, SWANSEA  
SA7 9EJ,  
UNITED KINGDOM  
TEL: (01792) 702701

### MIDDLE EAST

**BAHRAIN**  
Moon Stores  
No.16, Bab Al Bahrain Avenue,  
P.O. Box 247, Manama 304,  
State of BAHRAIN  
TEL: 17 211 085

**IRAN**  
MOCO INC.  
No.41 Nike St. DeShariyat Ave.,  
Robonyeh Cerah Miradmad  
Tehran, IRAN  
TEL: (021) 285-4169

**ISRAEL**  
Halili P Greenspoon & Sons  
Ltd.  
8 Retzif Ha'aliya Hashmya St.  
Tel-Aviv-Yafo ISRAEL  
TEL: (03) 6823666

As of November 1, 2006 (ROLAND)

- \* Avoid touching or scratching the shiny underside (encoded surface) of the disc. Damaged or dirty CD-ROM discs may not read properly. Keep your discs clean using a commercially available CD cleaner.
- \* Microsoft and Windows are registered trademarks of Microsoft Corporation.
- \* Windows Vista is a trademark of Microsoft Corporation.
- \* Windows® is known officially as: "Microsoft® Windows® operating system."
- \* The screen shots in this document are used in compliance with the guidelines of the Microsoft Corporation.
- \* Apple and Macintosh are registered trademarks of Apple, Inc.
- \* Mac OS is a trademark of Apple, Inc.
- \* All product names mentioned in this document are trademarks or registered trademarks of their respective owners.
- \* In the interest of product improvement, the specifications and/or contents of this package are subject to change without prior notice.

Please also read the Readme\_E.htm provided on the V-Synth GT Driver CD-ROM.