



# **Technical Specifications**



# **V-TONE GM108**

True Analog Modeling 15-Watt Guitar Amp with 8" Speaker



## **EN V-TONE GM108**

### True Analog Modeling 15-Watt Guitar Amp with 8" Speaker

- Extremely versatile guitar amplifier with authentic analog amp modeling
- Powerful 20-Watt, 8" BUGERA speaker for true vintage sound
- Authentic analog modeling for 3 classic quitar amps, 3 speaker simulation models plus 3 gain modes—providing you with 27 classic sounds
- Wide-range Drive control for super-fat sounds with any pickup
- Ultra-musical 3-band EQ for ultimate sound shaping
- CD input allows you to play along with your favorite music
- Powerful Headphone output with speaker simulation
- High-quality components and exceptionally rugged construction ensure long life
- Conceived and designed by BEHRINGER Germany

#### **Specifications**

Audio Inputs	
Guitar input connector	1/4" TS mono connector
CD input connector	1/4" TRS stereo connector
Audio Outputs	
Headphone output connector	¼" TRS stereo connector
System Specifications	
Power amp output	15 Watts RMS into 4 Ohms
Loudspeaker	
Туре	8" vintage design guitar speaker
Impedance	4 Ohms
Power handling	20 Watts

ins Voltage	
USA/Canada	120 V∼, 60 Hz
Europe/U.K./Australia	230 V~, 50 Hz
Japan	100 V∼, 50 - 60 Hz
nensions/Weight Dimmensions (H x W x D)	approx. 13 ½ x 14 ½ x 6 ¾"
Dillillielisiolis (H X W X D)	approx. 322 x 357 x 162 mm
Weight	approx. 11 lbs 3 oz / 5.15 kg

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to existing products without prior notice. Specifications and appearance may differ from those listed or illustrated.